



Coded keypad with push button or hands-free proximity reader

- To control an insulated door
- Hands-free proximity reader
- Same look & feel as the V4 intercom
- Change codes and manage key fobs remotely



CODED KEYPAD 12 backlit buttons with push button and hands-free proximity reader

CODED KEYPAD PRODUCT RANGE

| CODED KEYPADS | |
|---------------|---|
| 04-0109 | Coded keypad with 12 backlit buttons, a push button and a hands-free proximity reader - Stainless steel finish |
| 04-0112 | Coded keypad with 12 backlit buttons, a push button and a hands-free proximity reader - Brass finish |
| ACCESSORIES | |
| 12-0165 | Wall box for coded keypad with 12 backlit buttons, a push button and a hands-free proximity reader - Stainless steel finish |



TECHNICAL CHARACTERISTICS

| POWER SUPPLY |
|---|
| For the keypad through central unit 12 to 24 V DC |
| WIRING |
| Central unit - Coded keypad 4 wires (2 twisted pairs) - Ø 8/10e - Max distance: 100 m |
| DIMENSIONS (L X H X D) |
| Coded keypad 120 x 250 x 2,5 mm Wall box 101 x 220 x 37 mm |
| ENVIRONMENT |
| Operating temperature -20° C to +60° C Protection class Keypad IP55 |

| MANAGEMENT MODE | |
|---|---------------|
| Real-time (with transmission module) | ✓ |
| MANAGEMENT | |
| 1 door controller (with central unit 03-0102) | ✓ |
| FEATURES | |
| Free access time slots | ✓ |
| Event log | ✓ |
| Master key | ✓ |
| Alerts | ✓ |
| Code | 40 |
| PROXIMITY READER | |
| Max number of key fobs (central unit) | 1 000 / 7 000 |
| Compatible with hands-free key fobs | ✓ |